

CP-HAS-S1-W

Smart Wi-Fi Smoke Sensor

- Alarm: when the detected smoke concentration exceeds, Red LED will flash quickly and the buzzer will give out quick “Di-Di-Di” alarm sounds.
- Hush: when the smoke alarm is alarming, press the hush button, the device will enter hush mode for about 10 minutes; if in low battery warning status, press the hush button, the device will enter hush mode for about 12 hours.
- Low Battery: When the battery power becomes low, the red LED will flash once and the smoke alarm will issue “Di” warning sound once every 53 seconds.
- Report alarms to smart phone in real time.
- Support Wi-Fi Protocol: IEEE 802.11 b/g/n.



About CP PLUS

The brand that is on its way to lead the world when it comes to the security and surveillance industry, CP PLUS, keeps bombarding the market with the most reliable range of products that have been designed carefully and methodically to automate the whole surveillance and security process, no matter how big your premises are.

It was the initiative to help the public in the area where they are the most vulnerable and to empower the sense of safety in our hearts that had conceptualized CP PLUS. And embarking on its mission to make the world a safer and more secure place has taken the brand's journey to unprecedented levels even when compared to international competitors.

THINK SECURITY
THINK CP PLUS

 CP PLUS



CP-HAS-S1-W

Smart Wi-Fi Smoke Sensor

Feature	Specification
Working Voltage	DC 3V (CR123A lithium Battery)
Alarm Indication	Red LED
Sound Level	≥85dB/3m
Sensor Type	Infrared Photoelectric
Networking	Wi-Fi 2.4GHz
Wi-Fi Protocol	IEEE 802.11 b/g/n
Working Temperature	-10°C ~ +50°C
Working Humidity	≤95% RH (no condensation)
Dimension	Ø48mm x H51mm